

TITLE: Breast Biopsy and Therapy System for Magnetic Resonance Imagers

The enclosed Patent Application is based upon Provisional Application for Patent 60/202,821, filed on 5/8/2000.

CROSS-REFERENCE TO RELATED APPLICATIONS: Not Applicable

STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT: Not applicable.

REFERENCE TO A MICROFICHE APPENDIX: Not Applicable

FIELD OF THE INVENTION

This invention relates to MRI-guided breast biopsies and therapy. It describes an apparatus for performing breast biopsies and/or therapy inside any type of MRI scanner, including high field "closed" MRI systems. It includes a RF receive coil for magnetic resonance imaging (MRI) of the breast and a mechanical device for positioning interventional instruments inside the MRI scanner. Real time MR imaging is used to guide and monitor the interventional procedure.

BACKGROUND OF THE INVENTION:

Magnetic resonance imaging (MRI) is an important clinical modality for the detection and delineation of breast carcinoma. Its high sensitivity allows detection and characterization of breast lesions not seen by other imaging technologies. However, current MRI systems are not optimized for breast biopsy. Low field open MRI systems provide access to the patient but have limited imaging performance for detecting and characterizing breast carcinoma. High field "closed" systems provide superior imaging performance but have limited access to the patient, preventing the use of real time imaging to guide the biopsy.

Existing breast biopsy systems for high field closed MRI systems require that the patient be removed from the scanner in order to perform the biopsy. This prevents the use of real time

imaging to guide the biopsy. Errors in the instrument trajectory cannot be detected which can reduce the diagnostic quality of the tissue sample.

U.S. Patent No. 6,163,717 issued in the name of Su, discloses an open breast coil for interventional MRI. Su does not disclose methods for incorporating breast compression plates into the coil or a means to position breast biopsy or therapy instruments inside the MRI scanner. Su's design is most useful for a lateral access to the breast. Access from the front is more limited than the present invention. Also, Su's design does not teach a robust means of supporting the patient weight while maintaining adequate access to the breast for performing interventional procedures.

U.S. Patent No. 5,706,812, granted to Strenk, teaches a MRI breast biopsy coil with a transverse access portal and a stereotactic frame for guiding a biopsy needle. The coil is a linear coil that has reduced sensitivity compared to quadrature or phased array imaging coils. The design does not allow breast compression laterally or in the head/feet direction. Also, the design does not teach means for positioning instruments in the MRI scanner or methods of performing breast biopsies inside high field MRI scanners with limited access to the patient.

U.S. Patent No. 5,755,667, issued in the name of Friedrich, discloses a MRI breast coil with compression plates. The coil is not open and does not allow performance of breast biopsies while the patient remains inside the MRI scanner.

U. S. Patent No. 5,437,280, issued to Hussman, teaches a localizer apparatus suitable for guidance of medical instruments to lesions in the breast using a MR visible coordinate system. The patent does not teach design of open breast imaging coils or methods of performing breast biopsies while the patient remains inside the MRI scanner.

U. S. Patent No. 5,678,549, granted to Heywang-Koebrunner, discloses a stereotactic compression device and imaging coil for performing MRI guided breast biopsies. The patent does not disclose breast coil designs that are open in the front, or a means of performing breast biopsies inside high field MRI systems. The device requires that the patient be removed from the scanner to perform the biopsy.

U. S. Patent No. 5,690,108, issued to Chakeres, teaches an apparatus for aligning an instrument along a desired trajectory to a target using MR imaging. It does not teach open access imaging coils for breast biopsy or a method to insert a variety of instruments into the patient inside the MRI scanner.

U.S. Patent No. 5,569,266, granted to Siczek, discloses a MRI guided breast biopsy device, including an imaging coil and a device for positioning a biopsy instrument in the breast. The patent does not disclose means to insert instruments into the patient while they remain inside the scanner. The device requires that the patient be removed from the scanner to insert the biopsy instrument.

SUMMARY OF THE INVENTION

To overcome the limitations of the known apparatus and medical procedures we have discovered a novel apparatus that provides important advantages over the prior art. The subsequently disclosed and claimed invention discloses a device for performing MRI guided breast biopsies and/or therapy without having to remove the patient from the scanner. The device can be used in any type of MRI system, including both low field open MRI systems and high field "closed" MRI systems. The device allows a variety of interventional procedures to be performed on the breast using real time MR imaging for guidance and monitoring.

According to one aspect of the present invention, the MRI biopsy device includes a RF receiver coil for imaging both breasts, said coil being open in the front and the side in order to provide access to the breast while the patient remains inside the scanner. The patient lies prone on top of the coil and the breasts extend down into the coils. In high field closed scanners the patient is put feet first into the cylindrical magnet and the procedure is performed from the front of the magnet through the opening in the front of the coil. Alternatively, the patient may be put into the scanner head first and the procedure is performed from the rear of the magnet through the opening in the front of the coil.

According to another aspect of the invention, the breast coil includes compression plates for compressing the breast during imaging and holding it rigidly in place during the biopsy or therapy. The compression plates are designed such that they may compress the breast in either the head/feet direction or laterally. The compression plates include holes through which the

interventional instrument is inserted into the breast. In one embodiment the compression plate includes a grid of finely-spaced holes through which the instrument is inserted. In another embodiment the compression plate includes large rectangular access windows through which the instrument is inserted.

According to a further aspect of the present invention, the device includes a mechanical apparatus for positioning an instrument inside the MRI system. In the preferred embodiment an instrument is attached to the mechanical positioning apparatus and the position of the instrument is manipulated by a plurality of mechanical means. The controls for the mechanical instrument positioning device may be substantially removed from the instrument positioning assembly, providing remote control of the instrument position. Remote control operation is especially advantageous in the cylindrical magnets of high field "closed" MRI systems. Mechanical means for positioning the instrument inside the MRI scanner allows the use of real time imaging to guide the alignment of the trajectory and the insertion of the instrument into the lesion.

Alternate embodiments include positioning thermal therapy or drug delivery probes inside the MRI system, using real-time imaging to guide and/or monitor the procedure. Another embodiment includes remote control operation of interventional instruments inside the MRI scanner and robotic control of the instrument position.

DESCRIPTION OF THE DRAWINGS

Fig. 1 is a view of the bilateral breast receiver coil with open access from the front and lateral directions. Fig. 1 also shows the compression plates used to secure the breast in the coil.

Fig. 2 shows the conductor geometry for the RF antennae in the bilateral breast receiver coil.

Fig. 3 shows the mechanical positioning device that is used to position an interventional instrument such as a biopsy needle or therapy probe in the MRI scanner.

Fig. 4 shows the mechanical positioning device integrated into the breast imaging coil assembly.

Fig. 5 shows a mechanical positioning device with a rotational degree of freedom about the Y-axis.

DETAILED DESCRIPTION OF THE INVENTION:

Fig. 1 shows the breast imaging coil assembly. The patient lies prone on top of the coil with the sternum resting on the central support beam 190. The patient's head is supported by head support 140. The patient's shoulders are supported by shoulder supports 130. The patient's breasts extend down into the RF coil assemblies 120. In a high field closed MRI scanner the patient may be inserted feet first into the cylindrical magnet and the procedure performed from the front of the magnet through the opening in the front of the coil. Alternatively, the patient may be put into the scanner head first and the procedure performed from the rear of the magnet through the opening in the front of the coil.

The breasts are compressed by compression plates 110 or 150. Said compression plates may compress the breast either in the head/feet direction (z axis) or the lateral direction (x axis). The compression plates may be one of two types; compression plate 110 consists of a plastic plate with a grid of finely-spaced needle guide holes. In Fig. 1 the compression plate 110 is shown oriented along the lateral direction but it may also compress the breast in the head/feet direction. Compression plate 150 consists of a plastic plate with large rectangular access windows, which is advantageous when a mechanical device is used for positioning the interventional instrument, as is described below. Compression plate 150 can be made MR visible by embedding or attaching MR visible material such as tubes filled with water to said compression plate. Fig. 1 shows compression plate 150 compressing the breast in the head/feet direction but it may also be used in the lateral direction.

Referring to Fig. 1b, the compression plates are secured to the breast coil housing by means of clamps or latching mechanism 160 which slide in and out of the coil housing by means of side rails 170 embedded in the coil housing. The compression plates may also be secured to the coil cross-members 120 by means of clamps or latching mechanism 180. Compression plate 110 includes MR visible markers 112. The position of the markers 112 relative to the tumor is measured on the MR images. The proper needle entry hole is then determined by determining which hole in the compression plate is closest to the desired entry point, as is known in the art (see for example U.S. Patents 5,678,549 and 5,437,280).

Compression plates 110 and 150 may also be used for laterally directed biopsies performed outside the magnet as is known in the art (see for example Katharina, et al., Radiology, 1997; 204: 667-675).

The housing for the coil also includes an abdominal support (100), and head and shoulder supports (130,140). The head support 140 and shoulder supports 130 may be elevated at an angle in order to provide additional access to the breast from the front.

Fig. 2 shows a schematic view of the RF antennas that are enclosed in the breast receiver coils 120. The RF antenna conductor elements 10 are configured to form four loop antennae spaced apart vertically and horizontally sufficiently to accommodate the patient's breast 50. The RF antenna housings are open in both the lateral and front (head) directions, as shown in Fig 1. This provides access to the breast either from the front or the side. The patient's breasts are inserted through the top opening in the coils. The RF signals from each of the coils are conducted into an electronic interface 40 by means of cables 30. The coils may be electrically combined as a quadrature coil or as a 4-channel phased array coil. The RF signals from each of the coils are pre-amplified and combined as required in the electronic interface(s) 40, as is known in the art. The capacitors 20 are used to tune the coil to the proper operating frequency of the MRI scanner and to suppress unwanted eddy currents in the RF coils. Additional capacitors not shown in the electronic interfaces 40 are also used for tuning the coil to the proper operating frequency and impedance matching.

Fig. 2 shows the embodiment of the coil geometry for a high field MRI system with the magnetic field oriented along the z-axis. In low field "open" MRI systems the magnetic field is oriented along the y-axis. For this case, the coil assembly shown in Fig. 2 is rotated 90 degrees about the x-axis in order to maintain the proper orientation of the coil with respect to the direction of the magnetic field. The coil housing and compression plates require no modifications for this embodiment.

In an alternate embodiment the coil may consist of only 2 antennae, spaced apart either vertically or horizontally. This embodiment could provide improved access to the patient at the expense of imaging sensitivity.

Fig. 3 shows a manually operated mechanical apparatus for positioning instruments within the MRI scanner. The instrument 200 can be any one of a number of commercially available biopsy instruments. Alternatively, the instrument could be a therapy probe such as a RF, laser or cryogenic probe for thermal ablation of tumors or a drug delivery probe for localized delivery of drugs. In the embodiment shown in Fig. 3 the interventional instrument 200 is mounted to the instrument platform 220 by means of side rails 211 on said instrument 200 that slide into corresponding slots 212 on instrument platform 220 (see Fig. 3b). The instrument 200 may be rigidly secured to the instrument platform 220 by means of snaps 210 on said instrument. Said snaps mate with corresponding indentations in the instrument platform 220. An alternate embodiment uses clamps to secure the instrument 200 to the instrument platform 220. The instrument platform 220 includes a MR-visible needle guide 230 that is visible in the MR images, providing a means to align the instrument trajectory using real time MR imaging, as described below. The MR visible needle guide 230 consists of a cylinder with an inner cavity filled with MR visible material such as water, Gd-DPTA, or vegetable oil. Instrument platform 220 is attached to mounting block 240 by means of an inchworm gear 221. By rotating drive shaft 270 the inchworm gear 221 advances the instrument platform 220 such that the instrument 200 is advanced into the patient. In an alternate embodiment, the instrument may be manually inserted through the needle guide into the patient. Mounting block 240 is also used to control the vertical motion of the instrument platform. A rack 255 is attached to vertical support post 250 (Fig. 3b). A corresponding pinion gear in mounting block 240 (not shown) is used to drive the mounting block up and down the vertical support post 250. Drive shaft 260 on mounting block 240 is used to drive the pinion gear in said mounting block. The base-plate 280 of the instrument positioning device includes guide rails 295 and a threaded borehole 290.

With reference to Fig 4, the mechanical positioning device is mounted to the base of the breast-imaging coil. Base-plate 280 is attached to an acme screw 300 in the base of the imaging coil by means of threaded bore hole 290 through said base-plate. Acme screw 300 is used to move the base-plate 280 of the instrument positioning device in the left/right direction. In this manner rotational motion of said acme screw translates into linear motion of said base-plate. Drive shaft 310 is used to rotate the acme screw. Rails 295 in base-plate 280 travel along guide slots 320 in the base of the breast coil. Said rails and slots serve to guide base-plate 280 along the guide slots 320 and prevent twisting or rotation of the base-plate assembly.

Fig. 5 shows a mechanical positioning device with a rotational degree of freedom about the y-axis. This device enables the use of oblique trajectories to the target. Support post 250 is mounted on a rotatable gear 300. Gear 300 is rotated by a second gear 310. Gear 310 is rotated by means of drive shaft 320.

The desired trajectory to the target is determined from a preliminary set of MR images. There are a number of methods that can be used to align the trajectory of the instrument. In the simplest embodiment, the needle guide 230 is aligned with the desired trajectory by acquiring real time MR images in the plane of said trajectory and adjusting the position of said needle guide so that it is aligned with the desired trajectory in the MR images. In an alternate embodiment, real time MR images may be acquired in a plane perpendicular to the desired trajectory with the center of the imaging plane centered on the line defining the trajectory. The imaging plane is offset so that a cross sectional image of needle guide 230 is visible in the images. The position of the needle guide is then adjusted until the cross section of the needle guide is aligned with the desired trajectory in the images. Following trajectory alignment the instrument is inserted into the patient through said needle guide. Real time images are acquired in the plane of the instrument to verify that the instrument insertion trajectory is correct. Realignment of the instrument trajectory may be performed in real time based on feedback from the MR images. In this manner, misalignment in the trajectory or any other sources of error in the instrument position may be detected and compensated for in real time.

In high-field "closed" MRI systems the preferred embodiment is to locate the instrument positioning device in the front of the coil, thereby providing a means to insert the instrument from the direction of the patient's head. A lateral approach in a high field system is limited by the diameter of the magnet bore. In a low field "open" MRI system the instrument positioning device may be located either in the front or the side of the coil, providing a means to insert the instrument either from the front or lateral directions.

A plurality of positioning devices may be used to insert a plurality of instruments into one or both breasts in a single session. For example, two positioning devices could be used to insert instruments into both breasts, either from the front or the side. In another embodiment, a positioning device could be located in front of the coil and a separate positioning device could be located on the side of the coil, providing a means to insert instruments both from the head and

lateral directions. In a low field open MRI system up to four positioning devices could be used in a particular session, two in the front and one on each side of the patient.

The mechanical positioning device must not distort the magnetic field of the MRI scanner so all of its components must be non-ferrous. Also, the positioning device must not interfere with the RF and pulsed magnetic field gradients of the MRI system so the use of conductive components must be avoided. Preferred materials for construction of the positioning device include thermo-plastics and thermo-sets.

In an alternate embodiment, an inchworm gear may be used for vertical motion of the instrument platform. A rack and pinion drive mechanism may also be used for horizontal motion of the instrument platform.

Another alternate embodiment uses cables instead of drive shafts to move the positioning device. The cables may be used to rotate the gears which move the instrument platform, mounting block, base-plate and/or support post. Alternatively, the cables may be directly connected to the instrument platform, mounting block and/or base-plate. The cables would then apply a push/pull to these components, causing them to move along guide rails, guide slots and/or guide rods.

In another alternate embodiment the positioning device may be used to position other types of instruments, such as spring-loaded biopsy guns, thermal therapy probes, or drug delivery probes. The instrument platform 220 may be modified as required to accommodate instruments of a variety of shapes and sizes. Alternatively, a variety of adaptors could be designed to mate a variety of instruments to the instrument platform 220 shown in Fig. 3.

Another alternate embodiment is to electronically control the positioning device by means of MR compatible motors. Examples of MR compatible motors include piezoelectric motors, vacuum-actuated drivers or hydraulic drivers. Electronic control of the mechanical positioning device allows remote control operation of the instrument inside the MRI scanner. Robotic control of the instrument is accomplished by means of an interface such that the MRI scanner computer controls the motors that drive the instrument positioning device.

The invention has been described with reference to the preferred embodiment. Obviously, modifications and alterations will occur to others upon reading and understanding the preceding

detailed description. It is intended that the invention be construed as including all such modifications and alterations insofar as they come within the scope of the appended claims or the equivalents thereof.

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000